

## **Dimming Compatibility**

	Megaman Lamp	Megaman Lamp	Megaman Lamp	Megaman Lamp
Dimmer	3W GOLD FILAMENT ST LAMP	3w GOLD FILAMENT CLASSIC LAMP	3W GOLD FILAMENT GLOBE 95MM	3W GOLD FILAMENT GLOBE 125MM
	146409, 146482	146109, 146138	146249, 146267	146314, 146394
	-21			79
MK K1524 SW1	TBC	TBC	TBC	TBC
HAMILTON LEDSTAT100W	10 lamps	10 lamps	10 lamps	10 lamps
Varilight ZOJP250-P - Version 10+	10 lamps	10 lamps	10 lamps	10 lamps
Varilight V-PRO GRID Module for MK etc	10 lamps	10 lamps	10 lamps	10 lamps
Varilight JQP401W - Version 10+	10 lamps	10 lamps	10 lamps	10 lamps
Aurora AU-DSP400x	10 lamps	10 lamps	10 lamps	10 lamps
M2/CEF/RPP 1400DX	10 lamps	10 lamps	10 lamps	10 lamps
RPP/CEF DSP400 SW1	10 lamps	10 lamps	10 lamps	10 lamps
RPP/CEF DSP400 SW2	10 lamps	10 lamps	10 lamps	10 lamps
DETA \$1261	10 lamps	10 lamps	10 lamps	10 lamps

During operation some combinations of approved dimmers and LED lamps/fittings may exhibit a buzzing sound. This sound may be more pronounced in environments with very low DB levels and thus sound noisier.

Historically this noise may have come from vibrating components in the lamp, transformer and dimmer and the buzzing can still exist, but for different reasons. This could be due to the interaction of components from the circuitry in the dimmer and the lamp &/or driver. Additionally, the supply voltage can induce further noise which electronic circuitry is more sensitive too. Provided the supply voltage is within specification and the tested dimmers are published as compatible by both the



Dimmer recommended by Megaman, up to number of lamps stated.



Dimmer not recommended by Megaman.

TBC

To Be Confirmed due to tests pending.

Based on testing undertaken by Megaman. Megaman cannot accept responsibility for changes made by dimmer manufacturers. All information stated is correct at time of publication and is subject to change without prior notice. Please visit www.megamanuk.com for latest information.

Last Updated

20/12/2017