

## **Dimming Compatibility**

Dimmer	Megaman Lamp		Megaman Lamp	
	8W Siena Integrated Dim To Warm	8.5W Siena Integrated Square	13W Siena Dimming	13W Siena Dim to warm
	191406, 191617	191761, 191704, 191831, 191849	519206, 519248	191301
	mu	(Inn.)	8.	
HAMILTON LEDSTAT100W	X	X	TBC	TBC
Varilight ZOJP250-P - Version 10+	10 lamps	10 lamps	7 lamps	7 lamps
Varilight V-PRO GRID Module for MK etc	10 lamps	10 lamps	7 lamps	7 lamps
Varilight JQP401W - Version 10+	10 lamps	10 lamps	7 lamps	7 lamps
Aurora AU-DSP400x	10 lamps	10 lamps	7 lamps	7 lamps
M2/CEF/RPP 1400DX	10 lamps	10 lamps	7 lamps	7 lamps
RPP/CEF DSP400 SW1	10 lamps	10 lamps	7 lamps	7 lamps
RPP/CEF DSP400 SW2	10 lamps	10 lamps	7 lamps	7 lamps
DETA \$1261	10 lamps	10 lamps	7 lamps	7 lamps

During operation some combinations of approved dimmers and LED lamps/fittings may exhibit a buzzing sound. This sound may be more pronounced in environments with very low DB levels and thus sound noisier.

Historically this noise may have come from vibrating components in the lamp, transformer and dimmer and the buzzing can still exist, but for different reasons. This could be due to the interaction of components from the circuitry in the dimmer and the lamp &/or driver. Additionally, the supply voltage can induce further noise which electronic circuitry is more sensitive too. Provided the supply voltage is within specification and the tested dimmers are published as compatible by both the lamp/fitting and dimmer manufacturer. the buzzing does not signify a fault or warranty issue with the lamp and will not



Dimmer recommended by Megaman, up to number of lamps stated.



Dimmer not recommended by Megaman.

TBC

To Be Confirmed due to tests pending.