

An exceptional LED lay-in fitting for use in high footfall applications where access is limited and maintenance difficult. Non dimming driver included.



## 36W Berto 36W Square UGR22 LED Panel 4000K / 80 Non-Dim Driver

<b>Product Code</b>	130204
<b>International Model Number</b>	FPL70300V1-EX
<b>Description</b>	36W Berto 36W Square UGR22 LED Panel 4000K / 80 Non-Dim Driver
<b>Watts</b>	36W
<b>Colour Temperature</b>	4000K / 80
<b>Lumens</b>	3400lm
<b>Dimmable</b>	N
<b>Lamp life L70</b>	50,000hrs
<b>Lamp life L90</b>	25,000hrs
<b>Beam Angle</b>	110°
<b>Weight</b>	195g
<b>Dimensions</b>	595x595x13
<b>IP Rating</b>	IP20
<b>Shape</b>	Square
<b>Operating Temperature</b>	-30° to +40°

Last modified: 2021-02-11 17:24:51.

View online at <https://www.megamanuk.com/products/performa-led-fixtures/berto/130204/>