

The Megaman LED MR11 is an ideal replacement for halogen, providing significant energy savings and much less heat output. Excellent for use in display cabinets.

Driver: Megaman recommends Osram HTM70 Transformer, will run a min of 1 lamp and max of 2 lamps OR Phillips Certaline Transformer, will run a min of 1 lamp and max of 2 lamps.



| 4W GU4 MR11 12V 2800K | |
|-----------------------------------|---------------------|
| Product Code | 141178 |
| International Model Number | ER2304-20H36D |
| Description | LED 4W GU4 MR11 12V |
| Order in | 1 |
| Watts | 4 |
| Cap | GU4 |
| Operating Hours (L70) | 50000 |
| Operating Hours (L90) | 25000 |
| Colour Temp | 2800K |
| CRI | 80 |
| Lumens | 230lm |
| Intensity | 600cd |
| Dimming | No |
| Beam | 36 |
| Dimensions | 42 x 35 |
| Weight | 19g |
| Energy Class | A+ |
| Operating Temperature | -30°C to +40°C |

Last modified: 2016-10-21 15:11:14.

View online at <https://www.megamanuk.com/products/led-lamps/mr11/141178/>