

The dim to warm range of Megaman LEDs emit a warmer light when they are dimmed, from 2800K to 1800K, simulating the characteristics of incandescent and halogen lamps.

Driver: Megaman recommends Megaman Driver 141703. Tested on a standard switch. Please consult dimmer manufacturer for compatibility.



## 12W G53 AR111 24° Dim to Warm 36V 2800K-1800K

<b>Product Code</b>	141549
<b>International Model Number</b>	ER2712w-75H24D
<b>Description</b>	LED 12W G53 AR111 2800K-1800K
<b>Order in</b>	1
<b>Watts</b>	12W
<b>Cap</b>	G53
<b>Operating Hours (L70)</b>	50000
<b>Operating Hours (L90)</b>	40000
<b>Colour Temp</b>	2800K-1800K
<b>CRI</b>	82
<b>Lumens</b>	850lm
<b>Intensity</b>	5000cd
<b>Dimming</b>	Yes
<b>Beam</b>	24
<b>Dimensions</b>	58 x 111
<b>Weight</b>	230g
<b>Energy Class</b>	A
<b>Operating Temperature</b>	-30°C to +40°C

Last modified: 2016-10-21 15:17:27.

View online at <https://www.megamanuk.com/products/led-lamps/ar111/141549/>