

The Megaman LED Tube is compatible with traditional magnetic ballasts making it a perfect alternative to traditional T8 fluorescent tubes. Requires use of starter replacement, and shouldn't usually require re-wiring.



## 9W T8 G13 FLOURESCENT TUBE PROFESSIONAL LED 4000K

<b>Product Code</b>	174110
<b>International Model Number</b>	LT200090/mb-06v00
<b>Description</b>	9W T8 G13 FLOURESCENT TUBE PROFESSIONAL LED 4000K
<b>Watts</b>	9W
<b>Lamp Base</b>	G13
<b>Hrs Lamp Life (max)</b>	30,000
<b>Colour Temp</b>	4000K
<b>CRI</b>	80
<b>Lumens (lm)</b>	920
<b>Dimming</b>	No
<b>Dimensions (L x Dia mm)</b>	603x28 (2ft)
<b>Weight</b>	105g
<b>Energy Class</b>	A+
<b>Operating Temperature</b>	-10°C to +30°C

Last modified: 2021-02-26 17:33:39.

View online at <https://www.megamanuk.com/products/led-lamps/tube/174110/>